

FLNR_ID and FLSR_ID Dimensions

Amps	Series	Length Inches (mm)	Dia. Inches (mm)
8/10 – 30*	FLNR	2 (50.8)	9/16 (14.3)
1/2 – 30*	FLSR_ID	5 (127)	13/16 (20.6)
35 – 60	FLNR_ID	3 (76.2)	13/16 (20.6)
35 – 60	FLSR_ID	5-1/2 (139.7)	1-1/16 (27)
70 – 100	FLNR_ID	5-7/8 (149.2)	1-1/16 (27)
70 – 100	FLSR_ID	7-7/8 (200)	1-5/16 (33.3)
110 – 200	FLNR_ID	7-1/8 (181)	1-19/32 (40.5)
110 – 200	FLSR_ID	9-5/8 (244.5)	1-27/32 (46.8)
225 – 400	FLNR_ID	8-5/8 (219.1)	2-3/32 (53.2)
225 – 400	FLSR_ID	11-5/8 (295.3)	2-19/32 (65.9)
450 – 500	FLNR_ID	10-3/8 (263.5)	2-19/32 (65.9)
450 – 600	FLSR_ID	13-3/8 (339.7)	3-3/32 (78.6)

**FLNR amperages between 1/2 and 30A, and FLSR amperages below 1A, do not have an indicating window due to internal space limitations.*